Ver. 1.101 - Newly Added Functions

Excluding the STANDBY Button from Locked Panel Operations

The STANDBY button on the front panel can be used to put the R-1000 in standby mode even when panel operations are locked.

1. **Press the MENU button. The menu screen appears.**



2. **Touch [SYSTEM]. The menu screen for the system displays.**



3. **Touch [PANEL LOCK SETTINGS]. The screen for panel-operation lock settings appears.**



4. **Touch [STANDBY], then touch [UNLOCK]. The [STANDBY] button is excluded from panel operations subject to locking.**



5. **Touch [Lock]. Panel operations are locked.**
6. **Pressing and holding the STANDBY button for 2 seconds makes a message appear. Touching [Standby] on the screen puts the R-1000 in standby mode.**